

Parts needed to mount the OLEK extrusion



Extrusion (A)



LED strip (B)




Hanger (C)



Cover (D)



Gasket (E)



End cap (F)

Tools needed for mounting:


- drill
- screwdriver

WARNING! All LED strips should be connected to a 12 V or 24 V power supply.

IMPORTANT: The mounting instructions present the basic form of assembly.
More methods and related accessories can be found at www.KlusDesign.eu

- 1.** Drill a hole in the extrusion (A) to feed the power cable .


cross-section



top view




- 2.** Mount the LED strip (B) in the extrusion.



B

- 3.** Suspend the extrusion using the hangers (C) and a chosen suspension system. The hanger manual can be [downloaded at www.KlusDesign.eu](http://www.KlusDesign.eu)

cross-section



top view



- 5.** Connect power to the LED strip. Insert the cover (D). Seal the end cap (F) with the gasket (E), mount the entire assembly on the top of the extrusion.

